

# M300M1V10AI

BETTER BY DESIGN

## **Milli-Speed Sensor**

#### **Monitors Rotating Machinery**

Approved for explosive atmospheres: ATEX, IECEx, and CCCEx Zones 20, 21 & 22 for dust Zones 0, 1 & 2 for gas

#### Application:

The Milli-Speed Sensor with 4 - 20 mA output is designed to detect rotational speed on bucket elevators, conveyors, airlocks, mixers, fans, grinders and many other rotating machines. Totally sealed and simple to calibrate, the Milli-Speed works in the harshest of conditions.

#### METHOD OF OPERATION

An inductive sensing device located in the nose of the Milli-Speed enclosure will detect a metal target. This target can be an existing bolt head or device attached to a shaft, such as 4B's Whirligig<sup>®</sup> sensor mount. During installation, the Milli-Speed is set to the normal running RPM by simple magnetic calibration.



#### Features

- 4-20mA output
- Simple Magnetic Calibration
- Loop Powered (2 Wire)
- Totally Sealed Construction: Submersible
- Easy Installation with Whirligig<sup>®</sup> Sensor Mount
- SpeedMaster™ Compatible for Accurate Testing

#### **Options:**

- WG4A-BR Shaft mounting assembly, 4 pulses per revolution
- WG2A-BR Shaft mounting assembly, 2 pulses per revolution
- MAG2000M Magnetic shaft connector



Detailed specification, wiring diagrams and installation/operating instructions available upon request.

**4B BRAIME COMPONENTS LIMITED** - Hunslet Road, Leeds LS10 1JZ, UK Tel: +44 (0)113 246 1800 Fax: +44 (0)113 243 5021 Email: <u>4b-uk@go4b.com</u>

# Information subject to change or correction. May 2021

**Product Datasheet** 

BRAIME COMPONENTS

## M300M1V10AI

BETTER BY DESIGN

TECHNICAL SPECIFICATIONS	
Model	M300M1V10AI
Power supply:	17 - 30 VDC
Load:	500 Ohm (Typical)
Speed Range:	20 - 1,000 PPM (Pulses Per Minute)
Sensing Range:	Ferrous Target - (8 mm) Maximum
Detection range:	Ferrous Target = ≤ 8 mm, Non-ferrous ≤ 5 mm
Calibration:	Magnet
Output:	<ol> <li>Linear from 4-20mA</li> <li>Over Speed = 20mA (123% or more of calibrated speed)</li> <li>Calibrated Speed = 17 mA (100%)</li> <li>Zero Speed = 4mA (0-10% of Calibrated Speed)</li> </ol>
Output Accuracy:	+/- 0.2 mA
Response Time:	<1 Second (Typical)
Overall Resolution:	0.3% (22 Microamps)
Protection:	IP66 Dust and Water Tight (Fully Encapsulated)
Operating temperature range:	-15°C to +50°C
Certificates and approvals:	

#### CONNECTIONS



NOTE: Supply polarity to the Milli-Speed is not important and the load can be connected to either wire.

Detailed specification, wiring diagrams and installation/operating instructions available upon request.

Please refer to instruction manual for correct installation. Information subject to change or correction. May 2021  $\,$ 

www.go4b.com

**4B BRAIME COMPONENTS LIMITED** - Hunslet Road, Leeds LS10 1JZ, UK Tel: +44 (0)113 246 1800 Fax: +44 (0)113 243 5021 Email: <u>4b-uk@go4b.com</u>



## M300M1V10AI

BETTER BY DESIGN

## DIMENSIONS



Note: All dimensions are given in mm and inches

Detailed specification, wiring diagrams and installation/operating instructions available upon request.

Please refer to instruction manual for correct installation. Information subject to change or correction. May 2021

